

m o o o i

# NomNom Light

ODIN VISSER




Can. Not. Resist! The NomNom Light by Odin Visser is a contemporary lighting design that puts a smile on your face and a tingle in your belly. This modestly sized suspension light is the perfect example of the art of omission, while remaining distinctive. Two straight lines and a sphere that create the illusion of two chopsticks holding something delicious. As a stand-alone, there's no way around NomNom's playful elegance, but when multiplied in a bundle or in a row, it's simply irresistible. The NomNom Light makes us hungry for more! And with six colours to choose from, there's always a new flavour to try out.

## *Detailing*



The NomNom Light is compatible with our Wireless Wall Switch, for quick and easy dimming that gives you full control over the light output.


## *Colours*



Blossom



Ginger



Indigo



Nori



Ruby



Wasabi

# NomNom Light / NomNom Light 20

## Dimensions

22cm | 8.7"



## Product

**WIDTH** 22cm | 8.7"  
**HEIGHT** 75cm | 29.5"  
**DEPTH** 20cm | 7.9"  
**WEIGHT NETTO** 1kg | 2.2lbs

## Packaging

**WIDTH** 26cm | 10.2"  
**HEIGHT** 26cm | 10.2"  
**CUBAGE** 0.05m<sup>3</sup> | 1.86ft<sup>3</sup>  
**LENGTH** 78cm | 30.7"  
**WEIGHT** 3.5kg | 7.72lbs

## Technical CE / UL

### MATERIAL

Anodized aluminium frame with a glass sphere

### ENERGY LABEL

E

### LIGHTSOURCE TYPE

LED

### NUMBER OF LIGHTSOURCES

1

### DIAMETER SHADE

20cm | 7.9"

### FREQUENCY

50/60

### LIFETIME

50000 hours

### CABLE LENGTH

250cm | 98.4"

### CANOPY

Pebble III Black, ABS

### CHROM Y

0.3973

### CRI

91

### INSTALLATION REQUIRED

Yes

### LIGHTSOURCE INCLUDED

Yes

### SHAPE

Globe

### INPUT VOLTAGE

110-270V

### MAX POWER CONSUMPTION

8W

### CABLE COLOUR

Black

### SWITCH

No

### CHROM X

0.4443

### COLOUR TEMPERATURE

2800 K (max)

### LIGHT DIRECTION

All directions

**LIGHT OUTPUT**

637 lm

**DIMMING & LIGHTING CONTROL**

Wireless Wall Switch (dimmer), Mains / ELV dimming is not possible, DALI dt6, Push / Pulse dim on Line Voltage, Smart Home Integration (Zigbee)

*See last page for more information about the dimming possibilities.*



## *Dimming & Lighting Control*

### *Mains / ELV dimming is not possible*

Mains and/or ELV dimming is not possible. The wireless wall switch is advised for dimming in this case.

Compatible models: NomNom Light 20 CCC, NomNom Light 20 CE, NomNom Light 20 UL

---

### *Wireless Wall Switch (dimmer)*

With our Wireless Wall Switch, you'll have full control over your Moooi lighting design with one touch. Our Wireless Wall Switch comprises two components, a wall switch and radio device to put in the canopy of your Moooi lighting design. The Wall Switch can also be integrated in existing System 55 (i.e. Gira and Jung) or Decora style wall switches. Once the radio device is installed you will also have the possibility to control your light fixture with the Casambi App available in the Google Play and Apple app store. Within moments you can enjoy full and fluent dimming, all the way to dark.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL

---

### *DALI dt6*

The luminaire is dimmable by integrating it into a DALI network. This is an universal and professional standard in home automation systems with endless control possibilities and ease. We advise to hire a professional to integrate the luminaire into your DALI network.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL

---

### *Push / Pulse dim on Line Voltage*

The luminaire is dimmable by using an external momentary switch or pushbutton switch. The switch is usually mounted on an existing wall socket. In some cases a Phase or Control wire needs to be added to your home's wiring. The switch should be suitable for use with line voltage and of the type 'normal off - momentary on'. The luminaire dims perfectly when the switch makes and holds contact. A short press switches between on and off.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL

---

### *Smart Home Integration (Zigbee)*

By adding a Zigbee converter this light fixture can seamlessly integrate into a Zigbee 3.0-based smart home network, such as Philips Hue, Amazon Alexa, Google Home, Ikea Tradfri and Homey. This integration allows for wireless control and compatibility with other smart home systems, without the need to change your home's wiring. To enable this, simply add a Zigbee converter to your luminaire. We recommend the Sunricher Zigbee to Dali

Converter for its reliability and compatibility with the US 110 voltage or the Osram 4062172044776 Zigbee 3.0 DALI Converter LI for 210-220V Please note that this converter is sold by third-party vendors and not directly by Moooi and this should be installed by a professional electrician.

Compatible models: NomNom Light 20 CE, NomNom Light 20 UL

---